



FOSC-350C

FOSC gel-sealed in-line closure

The FOSC-350C in-line closure is a sealed fiber optic splice closure designed for cable joint applications in the telecom outside plant network. The closure is suitable for deployment in aerial, underground or direct buried environments.

Suitable for housing up to 96 splices, the closure comes complete with mass splicing trays and cable attachment devices.

Sealing is achieved via built-in gel technology, resulting in extremely convenient re-entry and re-sealing.

Features:

- ◆ Gel-sealing
- ◆ In-line design
- ◆ 2 cable ports each side
- ◆ Multi-port kit options available; see separate datasheet for FOSC-350C multi-port kit (TC-2057/SIP/ACS/1-04/09)
- ◆ Suitable for aerial, underground and direct buried applications
- ◆ Easy re-entry and re-closure mechanism with latches
- ◆ High density
- ◆ Wraparound
- ◆ Multiple splice tray options

Dimensions and capacities

Length(mm)	368
Width(mm)	182
Height(mm)	106
Splicing capacity	96
Cable range(mm)	8~20
Number of cable port	2 + 2

Ordering information

FOSC - 350C - **XXX** - **X** - **X** **X** **X**

Tray type

- 24** for 24 stacked splice protectors, tower style
- 12** thin tray for 12 splice protectors, tower style
- 48I** for 48 stacked splice protectors, side hinge
- 24I** thin tray for 24 splice protectors, side hinge

Number of trays

- 1-4** for type 24, 24I
- 1-8** for type 12
- 1-3** for type 48I

Number of splice protector SMOUV included

- | | | | |
|----------|----|----------|----|
| 0 | 0 | 4 | 48 |
| 1 | 12 | 5 | 60 |
| 2 | 24 | 6 | 72 |
| 3 | 36 | 8 | 96 |

Mounting Kit

- 0** no mounting kit
- 1** aerial mounting kit
- 2** wall mounting kit

Branch off

- 0** no branch off
(Includes 2 cable attachments for main cable)
- 1** one branch
- 2** two branch




Tray 24



Tray 12



Tray 48I



Tray 24I

Tyco Electronics, TE logo, SMOUV and FOSC are trademarks.

The information given herein, including drawings, illustrations and schematics which are intended for illustration purposes only, is believed to be reliable. However, Tyco Electronics makes no warranties as to its accuracy or completeness and disclaims any liability in connection with its use. Tyco Electronics' obligations shall only be as set forth in Tyco Electronics' Standard Terms and Conditions of Sale for this product and in no case will Tyco Electronics be liable for any incidental, indirect or consequential damages arising out of the sale, resale, use or misuse of the product. Users of Tyco Electronics products should make their own evaluation to determine the suitability of each such product for the specific application.

Raychem Shanghai Cable Accessories Ltd.
 287 Qinjiang Road, Shanghai, 200233 China
 Tel: 86-21-61067000 Fax: 86-21-64852522
www.tycoelectronics.com
 TC-2035/SIP/ACS/2-04/09